

## EU - TYPE EXAMINATION CERTIFICATE

Safety Device, Controlling Device or Regulating Device intended for use outside a potentially explosive atmosphere but required for or contributing to the safe functioning of Equipment and Protective Systems with respect to the risks of explosion Directive 2014/34/EU

EU - Type Examination Certificate Number: **SGS23ATEX0019 – Issue 2**

Product: **MTL4500 & MTL5500 Series Galvanic Isolators – Analogue Input modules**

Manufacturer: **Eaton Electric Limited**

Address: **Great Marlings, Butterfield, Luton, Bedfordshire, LU2 8DL United Kingdom**

This re-issued certificate extends EU Type Examination Certificate No. SGS23ATEX0019 to apply to product designed and constructed in accordance with the specification set out in the Schedule of the said certificate but having any variations specified in the Schedule attached to this certificate and the documents therein referred to.

SGS Fimko Oy, Notified Body number 0598, in accordance with Article 17 of Directive 2014/34/EU of the European Parliament and of the Council, dated 26 February 2014, certifies that this product has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of products intended for use in potentially explosive atmospheres given in Annex II to the Directive.

The examination and test results are recorded in confidential Report No. **See Certificate History**

Compliance with the Essential Health and Safety Requirements has been assured by compliance with:

**EN IEC 60079-0: 2018      EN 60079-11: 2012**

except in respect of those requirements listed at item 18 of the Schedule.

If the sign “X” is placed after the certificate number, it indicates that the product is subject to the Specific Conditions of Use specified in the schedule to this certificate.

This EU - TYPE EXAMINATION CERTIFICATE relates only to the design and construction of the specified product. Further requirements of the Directive apply to the manufacturing process and supply of this product. These are not covered by this certificate.

The marking of the product shall include the following:

|                                                                                               |                 |                                            |
|-----------------------------------------------------------------------------------------------|-----------------|--------------------------------------------|
|  II (1) GD | [Ex ia Ga] IIC  | -20°C ≤ Ta ≤ +60°C – All Models            |
|                                                                                               | [Ex ia Da] IIIC | -20°C ≤ Ta ≤ +65°C – MTL5541-T Model only  |
|  I (M1)    | [Ex ia Ma] I    | -40°C ≤ Ta ≤ +60°C – MTL5544D-L Model only |

SGS Fimko Oy Customer Reference No. **0703**

Project File No. **23/0605**

This document is issued by the Company subject to their General Conditions for Certification Services accessible at <http://www.sgs.com/en/Terms-and-Conditions.aspx>. Attention is drawn to the limitation of liability, indemnification and jurisdiction issues defined therein. Any holder of this document is advised that information contained herein reflects the Company's findings at the time of their intervention only and within the limits of Client's instructions, if any. It does not necessarily indicate that the equipment may be used in particular industries or circumstances. The Company's sole responsibility is to its Client and this document does not exonerate parties to a transaction from exercising all their rights and obligations under the transaction documents. This document cannot be reproduced except in full, schedule included, without prior written approval of the Company. Any unauthorized alteration, forgery or falsification of the content or appearance of this document is unlawful and offenders may be prosecuted to the fullest extent of the law.

**SGS Fimko Oy**

Takomotie 8  
FI-00380 Helsinki, Finland  
Telephone +358 (0)9 696 361  
e-mail [sgs.fimko@sgs.com](mailto:sgs.fimko@sgs.com)  
web site [www.sgs.fi](http://www.sgs.fi)

Business ID 0978538-5 Member of the SGS Group (SGA SA)



Mikko Välimäki  
SGS Fimko Oy

**Schedule 1 – MTL4541\* / MTL4544\* Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters**

**Certificate Number SGS23ATEX0019 – Issue 2**

**Description of Product**

The MTL4544\* Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters is designed to provide a floating d.c. supply for energising two conventional 2 or 3-Wire 4/20mA transmitters or a 'smart' transmitter in the hazardous area and repeat these currents in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area apparatus to the intrinsically safe circuits by the means of limitation of current and voltage. The apparatus also allows bi-directional signal communication between the hazardous and non-hazardous area by the connection of a hand-held communicator (HHC).

The MTL4544\* Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters comprises four isolating transformers that provide galvanic isolation between the hazardous and non-hazardous area circuitry, zener diode chains and resistors providing voltage and current limitation. The above, together with other electronic components, are mounted on a single printed circuit board (PCB) and housed in a moulded plastic enclosure. Polarised plug and sockets are provided for the hazardous and non-hazardous area connections. All models are fitted with a power indication LED.

The MTL4541\* Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters is a depopulated version of the MTL4544\* and has only one channel populated. Both the MTL4541\* and MTL4544\* available in a number of model variants, denoted by the last digit in the model number. All models variants are built on a common PCB.

**Model Range:**

| Model No. |                                                                           |
|-----------|---------------------------------------------------------------------------|
| MTL4541   | Single Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters |
| MTL4541B  | Single Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters |
| MTL4541P  | Single Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters |
| MTL4544   | Dual Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters   |
| MTL4544B  | Dual Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters   |

**Input / Output Parameters**

**MTL4541, MTL4541B, MTL4544 & MTL4544B Models Parameters**

Non-Hazardous Area Terminals 8, 9, 11, 12, 13 & 14

$$U_m = 253V$$

The apparatus is designed to operate on the above terminals from a d.c. supply voltage of up to 35V.

Hazardous Area Terminals 2 w.r.t. 1

or

Hazardous Area Terminals 5 w.r.t 4 (MTL4544 & MTL4544B only)

$$\begin{aligned} U_o &= 28V & C_i &= 0 \\ I_o &= 93mA & L_i &= 0 \\ P_o &= 0.65W \end{aligned}$$

Hazardous Area Terminals 3 w.r.t. 1

or

Hazardous Area Terminals 6 w.r.t 4 (MTL4544 & MTL4544B only)

$$\begin{aligned} U_o &= 1.1V & U_i &= 30V \\ I_o &= 53mA & I_i &= 121mA \\ P_o &= 15mW \\ C_i &= 0 \\ L_i &= 0 \end{aligned}$$

When an intrinsically safe source is connected to these terminals it should have a source resistance of  $U_i / I_i$  and the capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source.

Hazardous area terminals 2 and 5 must not be used when the source is connected to these terminals.

Hazardous Area Terminals 2 w.r.t. 3

or

Hazardous Area Terminals 5 w.r.t 6 (MTL4544 & MTL4544B only)

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 87mA & L_i = 0 \\ P_o = 0.61W & \end{array}$$

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values for either channel:

| GROUP                                            | CAPACITANCE<br>( $\mu$ F) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu$ H/ohm) |
|--------------------------------------------------|---------------------------|--------------------|-----------------------------------|
| Hazardous Area Terminals 2 w.r.t. 1 or 5 w.r.t 4 |                           |                    |                                   |
| IIC                                              | 0.083                     | 4.2                | 56                                |
| IIB*                                             | 0.65                      | 12.6               | 210                               |
| IIA                                              | 2.15                      | 33.6               | 444                               |
| I                                                | 3.76                      | 53.7               | 668                               |
| Hazardous Area Terminals 3 w.r.t. 1 or 6 w.r.t 4 |                           |                    |                                   |
| IIC                                              | 100                       | 12.8               | 2,438                             |
| IIB*                                             | 1,000                     | 47.8               | 8,932                             |
| IIA                                              | 1,000                     | 104.7              | 18,140                            |
| I                                                | 1,000                     | 156.2              | 28,229                            |
| Hazardous Area Terminals 2 w.r.t. 3 or 5 w.r.t 6 |                           |                    |                                   |
| IIC                                              | 0.083                     | 4.9                | 59                                |
| IIB*                                             | 0.65                      | 20.0               | 222                               |
| IIA                                              | 2.15                      | 40.9               | 469                               |
| I                                                | 3.76                      | 59.1               | 710                               |

Notes:

- The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than 1 $\mu$ F for Groups IIB, IIA & I and 600nF for Group IIC.

\* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

**MTL4541P Model Parameters**

Non-Hazardous Area Terminals 8, 9, 11, 12, 13 & 14

$$U_m = 253V$$

The apparatus is designed to operate on the above terminals from a d.c. supply voltage of 35V d.c.

Hazardous Area Terminals 2 w.r.t. 1

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 116.6mA & L_i = 0 \\ P_o = 0.82W \end{array}$$

Hazardous Area Terminals 3 w.r.t. 1

$$\begin{array}{ll} U_o = 1.1V & U_i = 30V \\ I_o = 53mA & I_i = 121mA \\ P_o = 15mW \\ C_i = 0 \\ L_i = 0 \end{array}$$

When an intrinsically safe source is connected to these terminals it should have a source resistance of  $U_i / I_i$  and the capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source.

Hazardous area terminal 2 must not be used when the source is connected to these terminals.

Hazardous Area Terminals 2 w.r.t. 3

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 107mA & L_i = 0 \\ P_o = 0.75W \end{array}$$

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values:

| GROUP                               | CAPACITANCE<br>( $\mu F$ ) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu H/\Omega$ ) |
|-------------------------------------|----------------------------|--------------------|---------------------------------------|
| Hazardous Area Terminals 2 w.r.t. 1 |                            |                    |                                       |
| IIC                                 | 0.083                      | 2.7                | 45                                    |
| IIB*                                | 0.65                       | 11.8               | 175                                   |
| IIA                                 | 2.15                       | 23.5               | 370                                   |
| I                                   | 3.76                       | 33.5               | 545                                   |
| Hazardous Area Terminals 3 w.r.t. 1 |                            |                    |                                       |
| IIC                                 | 100                        | 12.8               | 2,438                                 |
| IIB*                                | 1,000                      | 47.8               | 8,932                                 |
| IIA                                 | 1,000                      | 104.7              | 18,140                                |
| I                                   | 1,000                      | 156.2              | 28,229                                |
| Hazardous Area Terminals 2 w.r.t. 3 |                            |                    |                                       |
| IIC                                 | 0.083                      | 3.2                | 50                                    |
| IIB*                                | 0.65                       | 13.7               | 190                                   |
| IIA                                 | 2.15                       | 27.5               | 401                                   |
| I                                   | 3.76                       | 39.3               | 596                                   |

Notes:

- 1) The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- 2) The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than  $1\mu F$  for Groups IIB, IIA & I and  $600nF$  for Group IIC.

\* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

**16 Report Number**

See Certificate History

**17 Specific Conditions of Use**

None

**18 Essential Health and Safety Requirements**

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product:

| Clause | Subject                                            | Compliance                    |
|--------|----------------------------------------------------|-------------------------------|
| 1.2.7  | LVD type requirements                              | Manufacturer responsibility   |
| 1.2.8  | Overloading of equipment (protection relays, etc.) | User/Installer responsibility |
| 1.4.1  | External effects                                   | User/Installer responsibility |
| 1.4.2  | Aggressive substances, etc.                        | User/Installer responsibility |

**19 Drawings and Documents**

New drawings submitted for this issue of certificate.

| Number   | Sheet  | Issue | Date  | Description                    |
|----------|--------|-------|-------|--------------------------------|
| CI4541-1 | 1 of 8 | 5     | 12.23 | Parts List for MTL4541/MTL4544 |

Current drawings also associated with this certificate.

| Number     | Sheet   | Issue | Date     | Description                                            |
|------------|---------|-------|----------|--------------------------------------------------------|
| CI4541-1   | 2 of 8  | 5     | 07.09    | Circuit Diagram for the MTL 4541/4544                  |
| CI4541-1   | 3 of 8  | 5     | 07.09    | Circuit Diagram for the MTL 4541/4544                  |
| CI4541-1   | 4 of 8  | 5     | 1.18     | MTL4541/MTL4544 Track Layout                           |
| CI4541-1   | 4A of 8 | 5     | 1.18     | MTL4541/MTL4544 Track Layout                           |
| CI4541-1   | 5 of 8  | 6     | 1.13     | MTL4541 Component Layout                               |
| CI4541-1   | 6 of 8  | 2     | 1.07     | PCB Detail for TPL300                                  |
| CI4541-1   | 7 of 8  | 2     | 1.07     | PCB Detail for TPL301                                  |
| CI4541-1   | 8 of 8  | 8     | 2.23     | MTL4541 Certification Label Details - Baseefa          |
| CI4500-3   | 1 of 1  | 1     | 12.10    | MTL4500 and MTL5500 – Alternative Zener Diode (Panjit) |
| CI4500-6   | 1 of 1  | 1     | 20.12.10 | MTL4500 and MTL5500 – Conformal Coating                |
| CI4500-100 | 1 of 1  | 2     | 1.13     | MTL 4500 Case                                          |

The above drawings are associated with BAS23UKEX0026 and held with IECEx BAS 23.0013.

For certificate history for MTL4541\* / MTL4544\* Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters, see Baseefa06ATEX0156 Issue 11.

**Schedule 2 – MTL4541A / MTL4541AS Single Channel & MTL4544A /  
MTL4544AS Two Channel Current Repeater**

13

14

**Certificate Number SGS23ATEX0019 – Issue 2**

**15 Description of Product**

The MTL4544A Two Channel Current Repeater is designed to repeat up to two 4-20mA current signals from separately powered 4/20mA transmitters located in the hazardous area to unspecified apparatus in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area apparatus to the intrinsically safe circuits by the means of limitation of current and voltage. The apparatus also allows bi-directional signal communication between the hazardous and non-hazardous area by connection of a hand-held communicator (HHC).

The MTL4544A Current Repeater comprises four isolating transformers that provide galvanic isolation between the hazardous and non-hazardous area circuitry, fuses, Zener diodes and resistors providing voltage and current limitation on each channel. The above, together with other electronic components are mounted on a single printed circuit board (PCB) and housed in a moulded plastic enclosure. Polarised plug and sockets are provided for hazardous and non-hazardous area connections. The apparatus is fitted with a Power-on LED indication.

The MTL4541A Single Channel Current Repeater is a depopulated version of the MTL4544A and has only one channel populated.

Minor changes to the non-hazardous are circuitry of both models of the apparatus form the MTL4541AS Single Channel and MTL4544AS Two Channel Current Repeater. These models use the same common PCB and enclosure and in terms of intrinsic safety are identical.

**Input/Output Parameters**

Non-Hazardous Area Terminals 8, 9, 11, 12, 13 & 14)

$$U_m = 253V \text{ r.m.s.}$$

The circuit connected to non-hazardous area terminals 8, 9, 11, 12, 13 & 14 is designed to operate from a d.c. supply voltage of up to 35V.

Hazardous Area Terminals 2 w.r.t. 1 (Channel 1)

Or

Hazardous Area Terminals 5 w.r.t. 4 (Channel 2 – MTL4544A / 4544AS models only)

$$\begin{array}{ll} U_o = 8.6V \text{ (Diode)} & C_i = 0 \\ I_o = 0 & L_i = 0 \\ P_o = 0 & \end{array}$$

This output voltage does not contribute to the short circuit spark risk, but must be considered for the calculation of load capacitance.

Although the apparatus does not itself comply with the simple apparatus requirements of Clause 5.7 of EN 60079-11: 2012, when each hazardous area channel is connected in an intrinsically safe circuit the internal stored energy, voltage and current of the interface will not add more than the values specified in Clause 5.7 of EN 60079-11: 2012 to the parameters of the circuit into which it is connected.

Each hazardous area channel is also considered suitable for the connection of an external intrinsically safe source with a  $U_o = 30V$  and  $I_o = 100mA$  having a source resistance of  $U_o/I_o$  to be connected to hazardous area terminals 2 w.r.t. 1 - Channel 1 and 5 w.r.t. 4 – Channel 2.

The capacitance and either the inductance or inductance to resistance ratio ( $L/R$ ) of the hazardous area cable must not exceed the values as detailed in the original schedule or the certificate relating to the external intrinsically safe source.

Each channel must be considered as a separate intrinsically safe circuit.

Hazardous Area Terminals 5 w.r.t. 1 (Channels 1 & 2 combined with Terminals 2 & 4 connected together – MTL4544A / 4544AS models only)

$$\begin{array}{ll} U_o = 17.2V \text{ (Diode)} & C_i = 0 \\ I_o = 0 & L_i = 0 \\ P_o = 0 \end{array}$$

This output voltage does not contribute to the short circuit spark risk, but must be considered for the calculation of load capacitance.

The connection of channel 1 and 2 together is also considered suitable for the connection of an external intrinsically safe source with a  $U_o = 30V$  and  $I_o = 100mA$  having a source resistance of  $U_o/I_o$  to be connected to hazardous area terminals 5 w.r.t. 1.

The capacitance and either the inductance or inductance to resistance ratio ( $L/R$ ) of the hazardous area cable must not exceed the values as detailed in the original schedule or the certificate relating to the external intrinsically safe source.

#### Load Parameters

The capacitance and either the inductance or inductance to resistance ratio ( $L/R$ ) of the hazardous area load connected to the apparatus must not exceed the following values:

| GROUP                                                                                                 | CAPACITANCE<br>( $\mu F$ ) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu H/ohm$ ) |
|-------------------------------------------------------------------------------------------------------|----------------------------|--------------------|------------------------------------|
| Hazardous Area Terminals 2 w.r.t. 1 (Channel 1) or 5 w.r.t. 4 (Channel 2 – MTL4544A/44AS models only) |                            |                    |                                    |
| IIC                                                                                                   | 6.2                        | 5.01               | 1,351                              |
| IIB*                                                                                                  | 55                         | 20.06              | 5,406                              |
| IIA                                                                                                   | 1,000                      | 40.12              | 10,813                             |
| I                                                                                                     | 1,000                      | 65.82              | 17,740                             |
| Hazardous Area Terminals 5 w.r.t. 1 (Channels 1 & 2 combined – MTL4544A/44AS models only)             |                            |                    |                                    |
| IIC                                                                                                   | 0.36                       | 5.01               | 675                                |
| IIB*                                                                                                  | 2.11                       | 20.06              | 2,703                              |
| IIA                                                                                                   | 8.7                        | 40.12              | 5,406                              |
| I                                                                                                     | 12.16                      | 65.82              | 8,870                              |

\*Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

#### Notes:

- The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than  $1\mu F$  for Groups IIB, IIA & I and  $600nF$  for Group IIC.

#### 16 Report Number

See Certificate History

#### 17 Specific Conditions of Use

None

## **18 Essential Health and Safety Requirements**

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product:

| <b>Clause</b> | <b>Subject</b>                                     | <b>Compliance</b>             |
|---------------|----------------------------------------------------|-------------------------------|
| 1.2.7         | LVD type requirements                              | Manufacturer responsibility   |
| 1.2.8         | Overloading of equipment (protection relays, etc.) | User/Installer responsibility |
| 1.4.1         | External effects                                   | User/Installer responsibility |
| 1.4.2         | Aggressive substances, etc.                        | User/Installer responsibility |

## **19 Drawings and Documents**

| <b>Number</b> | <b>Sheet</b> | <b>Issue</b> | <b>Date</b> | <b>Description</b>                                     |
|---------------|--------------|--------------|-------------|--------------------------------------------------------|
| CI4541-2      | 1 of 8       | 1            | 10.08       | Parts List for MTL4541A/MTL4544A                       |
| CI4541-2      | 2 of 8       | 1            | 11.08       | Certification Diagram for MTL4544A & 4541A             |
| CI4541-2      | 3 of 8       | 1            | 11.08       | Certification Diagram for MTL4544A & 4541A             |
| CI4541-2      | 4 of 8       | 1            | 11.08       | MTL4541A & 4544A Track Layout                          |
| CI4541-2      | 5 of 8       | 2            | 1.13        | MTL4541A & MTL4544A Component Layout                   |
| CI4541-2      | 6 of 8       | 1            | 11.08       | PCB Detail for TPL300                                  |
| CI4541-2      | 7 of 8       | 1            | 11.08       | PCB Detail for TPL301                                  |
| CI4541-2      | 8 of 8       | 4            | 2.23        | MTL4541A Certification Label Details - Baseefa         |
| CI4500-3      | 1 of 1       | 1            | 12.10       | MTL4500 and MTL5500 – Alternative Zener Diode (Panjit) |
| CI4500-6      | 1 of 1       | 1            | 20.12.10    | MTL4500 and MTL5500 – Conformal Coating                |
| CI4500-100    | 1 of 1       | 2            | 1.13        | MTL 4500 Case                                          |

The above drawings are associated with BAS23UKEX0026 and held with IECEx BAS 23.0013.

For certificate history for MTL4541A / MTL4541AS Single Channel & MTL4544A / MTL4544AS Two Channel Current Repeater, see Baseefa08ATEX0321 Issue 3.

**Schedule 3 - MTL4541S, MTL4541T, MTL4544S & MTL4544D Repeater**

**13 Power Supplies, 4/20mA**

**14 Certificate Number SGS23ATEX0019 – Issue 2**

**15 Description of Product**

The MTL4544S Two Channel Repeater Power Supply, 4/20mA for ‘Smart’ Transmitters is designed to provides floating d.c. supplies for energising two ‘Smart’ 4/20mA Transmitters located in the hazardous area and repeat these currents in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area apparatus to the intrinsically safe circuits by means of limitation of current and voltage. The apparatus also allows bi-directional signal communication between the hazardous and non-hazardous area by the connection of a hand-held communicator (HHC).

The MTL4544S Two Channel Repeater Power Supply, 4/20mA for ‘Smart’ Transmitters comprises four isolating transformers that provide galvanic isolation between the hazardous and non-hazardous area circuitry, zener diode chains and resistors providing voltage and current limitation. The above, together with other electronic components are mounted on a single printed circuit board (PCB) and housed in a moulded plastic enclosure. Polarised plugs and sockets are provided for hazardous and non-hazardous area connections. LED indication is fitted to indicate power-on.

The MTL4541S Single Channel Repeater Power Supply, 4/20mA for ‘Smart’ Transmitters is a depopulated version of the MTL4544S and has only one channel populated.

The MTL4544D Repeater Power Supply, 4/20mA for 2 or 3 Wire Transmitters with two outputs is designed to provide a floating d.c. supplies for energising a 2 or 3-Wire 4/20mA Transmitter located in the hazardous area and repeat the current on two channels in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area apparatus to the intrinsically safe circuits by means of limitation of current and voltage. The apparatus also allows bi-directional signal communication between the hazardous and non-hazardous area by the connection of a hand-held communicator (HHC). The apparatus uses the same printed circuit board and enclosure as the MTL4544S but is populated with only one hazardous area transmitter connection and two non-hazardous area outputs fitted.

The MTL4541T Single Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters is similar to the MTL4541S but is fitted with different voltage and current limitation components and therefore has different output parameters.

**Model Range**

|          |                                                                             |
|----------|-----------------------------------------------------------------------------|
| MTL4541S | Single Channel Repeater Power Supply, 4/20mA for ‘Smart’ Transmitters       |
| MTL4541T | Single Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters   |
| MTL4544S | Two Channel Repeater Power Supply, 4/20mA for ‘Smart’ Transmitters          |
| MTL4544D | Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters with Two Outputs |

**Input / Output Parameters**

**MTL4541S, MTL4544S & MTL4544D Input / Output Parameters**

**Non-hazardous Area Terminals 8, 9, 11, 12, 13 & 14**

$$U_m = 253V \text{ r.m.s.}$$

The apparatus is designed to operate on non-hazardous area terminals 8, 9, 11, 12, 13 & 14 from a d.c. supply voltage of up to 35V.

**Hazardous Area Terminals 2 w.r.t. 1 (Channel 1)**

**Or**

**Hazardous Area Terminals 5 w.r.t. 4 (Channel 2 – MTL4544S model)**

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 93mA & L_i = 0 \\ P_o = 0.65W & \end{array}$$

Hazardous Area Terminals 3 w.r.t. 1 (Channel 1)

Or

Hazardous Area Terminals 6 w.r.t. 4 (Channel 2 – MTL4544S model)

$$\begin{array}{lll} U_o = 1.1V & U_i = 30V & C_i = 0 \\ I_o = 53mA & I_i = 121mA & L_i = 0 \\ P_o = 15mW & & \end{array}$$

Although the apparatus does not comply with the simple apparatus requirements of Clause 5.7 of EN 60079-11: 2012, when terminals 3 w.r.t. 1 or terminals 6 w.r.t. 4 (MTL4544S model only) are connected in an intrinsically safe circuit the internal stored energy, voltage and current of the interface will not add more than the values specified in Clause 5.7 of EN 60079-11: 2012 to the parameters of the circuit into which it is connected.

When an external intrinsically safe source is connected to these terminals it should have a source resistance of  $U_i / I_i$  and the capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source. Hazardous area terminals 2 and 5 must not be used when the source is connected.

Hazardous Area Terminals 2 w.r.t. 3 (Channel 1)

Or

Hazardous Area Terminals 5 w.r.t. 6 (Channel 2 – MTL4544S model)

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 87mA & L_i = 0 \\ P_o = 0.61W & \end{array}$$

Each channel must be considered as a separate intrinsically safe circuit.

The capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values for either channel:

| GROUP                                                             | CAPACITANCE<br>( $\mu F$ ) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu H/ohm$ ) |
|-------------------------------------------------------------------|----------------------------|--------------------|------------------------------------|
| Hazardous Area Terminals 2 w.r.t. 1 or 5 w.r.t. 4 (MTL4544S only) |                            |                    |                                    |
| IIC                                                               | 0.083                      | 4.2                | 56                                 |
| IIB*                                                              | 0.65                       | 12.6               | 210                                |
| IIA                                                               | 2.15                       | 33.6               | 444                                |
| I                                                                 | 3.76                       | 53.7               | 668                                |
| Hazardous Area Terminals 3 w.r.t. 1 or 6 w.r.t. 4 (MTL4544S only) |                            |                    |                                    |
| IIC                                                               | 100                        | 12.8               | 2,438                              |
| IIB*                                                              | 1,000                      | 47.8               | 8,932                              |
| IIA                                                               | 1,000                      | 104.7              | 18,140                             |
| I                                                                 | 1,000                      | 156.2              | 28,229                             |
| Hazardous Area Terminals 2 w.r.t. 3 or 5 w.r.t. 6 (MTL4544S only) |                            |                    |                                    |
| IIC                                                               | 0.083                      | 4.9                | 59                                 |
| IIB*                                                              | 0.65                       | 20.0               | 222                                |
| IIA                                                               | 2.15                       | 40.9               | 469                                |
| I                                                                 | 3.76                       | 59.1               | 710                                |

\* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

**Notes:**

- The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than  $1\mu F$  for Groups IIB, IIA & I and  $600nF$  for Group IIC.

### MTL4541T Input / Output Parameters

#### Non-hazardous Area Terminals 8, 9, 11, 13 & 14

$$U_m = 253V \text{ r.m.s.}$$

The apparatus is designed to operate on non-hazardous area terminals 8, 9, 11, 13 & 14 from a d.c. supply voltage of up to 35V.

#### Hazardous Area Terminals 2 w.r.t. 1

$$\begin{array}{ll} U_o = 22V & C_i = 0 \\ I_o = 167mA & L_i = 0 \\ P_o = 0.92W \end{array}$$

#### Hazardous Area Terminals 3 w.r.t. 1

$$\begin{array}{llll} U_o = 1.0V & U_i = 30V & C_i = 0 \\ I_o = 53mA & I_i = 121mA & L_i = 0 \\ P_o = 14mW \end{array}$$

Although the apparatus does not comply with the simple apparatus requirements of Clause 5.7 of EN 60079-11: 2012, when terminals 3 w.r.t. 1 are connected in an intrinsically safe circuit the internal stored energy, voltage and current of the interface will not add more than the values specified in Clause 5.7 of EN 60079-11: 2012 to the parameters of the circuit into which it is connected.

When an external intrinsically safe source is connected to these terminals it should have a source resistance of  $U_i / I_i$  and the capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source. Hazardous area terminal 2 must not be used when the source is connected.

#### Hazardous Area Terminals 2 w.r.t. 3

$$\begin{array}{ll} U_o = 22V & C_i = 0 \\ I_o = 145mA & L_i = 0 \\ P_o = 0.80W \end{array}$$

The capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values:

| GROUP                               | CAPACITANCE<br>( $\mu F$ ) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu H/ohm$ ) |
|-------------------------------------|----------------------------|--------------------|------------------------------------|
| Hazardous Area Terminals 2 w.r.t. 1 |                            |                    |                                    |
| IIC                                 | 0.165                      | 0.91               | 39                                 |
| IIB*                                | 1.14                       | 5.5                | 147                                |
| IIA                                 | 4.20                       | 10.7               | 322                                |
| I                                   | 6.00                       | 16.4               | 517                                |
| Hazardous Area Terminals 3 w.r.t. 1 |                            |                    |                                    |
| IIC                                 | 100                        | 12.8               | 2,438                              |
| IIB*                                | 1,000                      | 47.8               | 8,932                              |
| IIA                                 | 1,000                      | 104.7              | 18,140                             |
| I                                   | 1,000                      | 156.2              | 28,229                             |
| Hazardous Area Terminals 2 w.r.t. 3 |                            |                    |                                    |
| IIC                                 | 0.165                      | 1.49               | 45                                 |
| IIB*                                | 1.14                       | 7.5                | 174                                |
| IIA                                 | 4.20                       | 14.9               | 381                                |
| I                                   | 6.00                       | 22.5               | 575                                |

\* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- 1) The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- 2) The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than  $1\mu\text{F}$  for Groups IIB, IIA & I and  $600\text{nF}$  for Group IIC.

**16 Report Number**

See Certificate History

**17 Specific Conditions of Use**

None

**18 Essential Health and Safety Requirements**

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product:

| Clause | Subject                                            | Compliance                    |
|--------|----------------------------------------------------|-------------------------------|
| 1.2.7  | LVD type requirements                              | Manufacturer responsibility   |
| 1.2.8  | Overloading of equipment (protection relays, etc.) | User/Installer responsibility |
| 1.4.1  | External effects                                   | User/Installer responsibility |
| 1.4.2  | Aggressive substances, etc.                        | User/Installer responsibility |

**19 Drawings and Documents**

New drawings submitted for this issue of certificate.

| Number   | Sheet  | Issue | Date  | Description                                                               |
|----------|--------|-------|-------|---------------------------------------------------------------------------|
| CI4541-3 | 1 of 8 | 5     | 12.23 | Parts List for MTL4541S, MTL5541S, MTL4544S, MTL5544S, MTL4544D, MTL5544D |

Current drawings also associated with this certificate.

| Number    | Sheet  | Issue | Date  | Description                                                                                  |
|-----------|--------|-------|-------|----------------------------------------------------------------------------------------------|
| CI4541-3  | 2 of 8 | 2     | 10.12 | Circuit Diagram for the MTL4541S, MTL5541S, MTL4544S, MTL5544S, MTL4544D, MTL5544D, MTL4541T |
| CI4541-3  | 3 of 8 | 2     | 10.12 | Circuit Diagram for the MTL4541S, MTL5541S, MTL4544S, MTL5544S, MTL4544D, MTL5544D, MTL4541T |
| CI4541-3  | 4 of 8 | 1     | 6.09  | Track Layout for MTL4541S, MTL5541S, MTL4544S, MTL5544S, MTL4544D, MTL5544D                  |
| CI4541-3  | 5 of 8 | 3     | 1.14  | Component Layout for MTL4541S, MTL4541T, MTL5541S, MTL4544S, MTL5544S, MTL4544D, MTL5544D    |
| CI4541-3  | 6 of 8 | 1     | 6.09  | PCB Detail for TPL300                                                                        |
| CI4541-3  | 7 of 8 | 1     | 6.09  | PCB Detail for TPL301                                                                        |
| CI4541-3  | 8 of 8 | 6     | 2.23  | MTL4541S, MTL4541T, MTL4544S, MTL4544D Certification Label Details - Baseefa                 |
| CI4541T-1 | 1 of 1 | 1     | 1.13  | Parts List for MTL4541T                                                                      |
| CI4500-3  | 1 of 1 | 1     | 12.10 | MTL4500 and MTL5500 – Alternative Zener Diode (Panjit)                                       |

---

| Number     | Sheet  | Issue | Date     | Description                             |
|------------|--------|-------|----------|-----------------------------------------|
| CI4500-6   | 1 of 1 | 1     | 20.12.10 | MTL4500 and MTL5500 – Conformal Coating |
| CI4500-100 | 1 of 1 | 2     | 1.13     | MTL 4500 Case                           |

The above drawings are associated with BAS23UKEX0026 and held with IECEx BAS 23.0013.  
For certificate history for MTL4541S, MTL4541T, MTL4544S & MTL4544D Repeater Power Supplies, 4/20mA, see Baseefa09ATEX0155 Issue 6.

**Schedule 4 – MTL4541Y Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters**

13

14 **Certificate Number SGS23ATEX0019 – Issue 2**

**15 Description of Product**

The MTL4541Y Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters is designed to provide a floating d.c. supply for energising a conventional 2 or 3-Wire 4/20mA Transmitter in the hazardous area and repeat these currents in the non-hazardous area, whilst restricting the transfer of energy from unspecified non-hazardous area equipment to the intrinsically safe circuits by means of limitation of current and voltage. The equipment also allows bi-directional signal communication between the hazardous and non-hazardous area by connection of a hand-held communicator (HHC).

The MTL4541Y Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters comprises two isolating transformers that provide galvanic isolation between the hazardous and non-hazardous area circuitry, zener diode chains and resistors providing voltage and current limitation. The above, together with other electronic components, are mounted on a single printed circuit board (PCB) and housed in a moulded plastic enclosure. Polarised plug and sockets are provided for hazardous and non-hazardous area connections. A LED is fitted to provide power on indication.

**Input / Output Parameters**

**Non-Hazardous Area Terminals 8, 9, 12, 13 & 14**

$$U_m = 253V$$

The apparatus is designed to operate on the above terminals from a d.c. supply voltage of up to 35V.

**Hazardous Area Terminals 2 w.r.t. 1**

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 93mA & L_i = 0 \\ P_o = 0.65W & \end{array}$$

**Hazardous Area Terminals 3 w.r.t. 1**

$$\begin{array}{lll} U_o = 1.1V & C_i = 0 & U_i = 30V \\ I_o = 53mA & L_i = 0 & I_i = 121mA \\ P_o = 15mW & \end{array}$$

When an intrinsically safe source is connected to these terminals it should have a source resistance of  $U_i / I_i$  and the capacitance and either the inductance or inductance to resistance ratio ( $L/R$ ) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source.

Hazardous Area Terminal 2 must not be used when the source is connected to these terminals.

**Hazardous Area Terminals 2 w.r.t. 3**

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 87mA & L_i = 0 \\ P_o = 0.61W & \end{array}$$

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values:

| GROUP                               | CAPACITANCE<br>( $\mu$ F) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu$ H/ $\Omega$ ) |
|-------------------------------------|---------------------------|--------------------|------------------------------------------|
| Hazardous Area Terminals 2 w.r.t. 1 |                           |                    |                                          |
| IIC                                 | 0.083                     | 4.2                | 56                                       |
| IIB**                               | 0.65                      | 12.6               | 210                                      |
| IIA                                 | 2.15                      | 33.6               | 444                                      |
| I                                   | 3.76                      | 53.7               | 668                                      |
| Hazardous Area Terminals 3 w.r.t. 1 |                           |                    |                                          |
| IIC                                 | 100                       | 12.8               | 2,438                                    |
| IIB**                               | 1,000                     | 47.8               | 8,932                                    |
| IIA                                 | 1,000                     | 104.7              | 18,140                                   |
| I                                   | 1,000                     | 156.2              | 28,229                                   |
| Hazardous Area Terminals 2 w.r.t. 3 |                           |                    |                                          |
| IIC                                 | 0.083                     | 4.9                | 59                                       |
| IIB**                               | 0.65                      | 20.0               | 222                                      |
| IIA                                 | 2.15                      | 40.9               | 469                                      |
| I                                   | 3.76                      | 59.1               | 710                                      |

\*\* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than 1 $\mu$ F for Groups IIB, IIA & I and 600nF for Group IIC.

## 16 Report Number

See Certificate History

## 17 Specific Conditions of Use

None

## 18 Essential Health and Safety Requirements

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product:

| Clause | Subject                                            | Compliance                    |
|--------|----------------------------------------------------|-------------------------------|
| 1.2.7  | LVD type requirements                              | Manufacturer responsibility   |
| 1.2.8  | Overloading of equipment (protection relays, etc.) | User/Installer responsibility |
| 1.4.1  | External effects                                   | User/Installer responsibility |
| 1.4.2  | Aggressive substances, etc.                        | User/Installer responsibility |

---

**19 Drawings and Documents**

| Number     | Sheet  | Issue | Date  | Description                                           |
|------------|--------|-------|-------|-------------------------------------------------------|
| CI4500-100 | 1 of 1 | 2     | 1.13  | MTL 4500 Case                                         |
| CI4541Y-1  | 1 & 2  | 1     | 11.14 | Circuit Diagram for the MTL 4541Y                     |
| CI4541Y-2  | 1 & 2  | 1     | 10.14 | MTL4541Y Parts List                                   |
| CI4541Y-3  | 1 of 1 | 1     | 11.14 | Track Layout for MTL4541Y                             |
| CI4541Y-4  | 1 & 2  | 1     | 10.14 | MTL4541Y Component Layout                             |
| CI4541Y-5  | 1 of 1 | 1     | 10.14 | PCB Detail for TPL300                                 |
| CI4541Y-6  | 1 of 1 | 1     | 10.14 | PCB Detail for TPL301                                 |
| CI4541Y-7  | 1 of 1 | 3     | 2.23  | MTL4541Y Certification Label Details – Baseefa – Ex i |

The above drawings are associated with BAS23UKEX0026 and held with IECEx BAS 23.0013.

For certificate history for MTL4541Y Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters, see Baseefa15ATEX0032 Issue 1.

**Schedule 5 – MTL4541YA Single Channel Current Repeater, 4/20mA Passive  
Input for Smart Transmitters**

13

14 **Certificate Number SGS23ATEX0019 – Issue 2**

**15 Description of Product**

The MTL4541YA Single Channel Current Repeater, 4/20mA Passive Input for Smart Transmitters is designed to repeat a current signal from a separately powered 4/20mA transmitter located in the hazardous area to unspecified equipment location in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area equipment to the intrinsically safe equipment by means of voltage and current limitation. The equipment also allows bi-directional signal communication between the hazardous and non-hazardous area by connection of a hand-held communicator (HHC).

The equipment comprises two isolating transformers that provide galvanic isolation between the hazardous and non-hazardous area circuitry, fuses, diodes, zener diodes and resistors providing voltage and current limitation. The above, together with other electronic components, are mounted on a single printed circuit board (PCB) and housed in a moulded plastic enclosure. Polarised plug and sockets are provided for hazardous and non-hazardous area connections. The equipment is fitted with a power-on LED indication.

**Input / Output Parameters**

**Non-Hazardous Area Terminals 8, 9, 12, 13 & 14**

$$U_m = 253V$$

The apparatus is designed to operate on the above terminals from a d.c. supply voltage of up to 35V.

**Hazardous Area Terminals 2 w.r.t. 1**

$$\begin{array}{ll} U_o = 8.6V \text{ (Diode)} & C_i = 0 \\ I_o = 0 & L_i = 0 \\ P_o = 0 \end{array}$$

This output voltage does not contribute to the short circuit spark risk, but must be considered for the calculation of load capacitance.

Although the apparatus does not itself comply with the simple apparatus requirements of Clause 5.7 of EN 60079-11: 2012, when the hazardous area terminals are connected in an intrinsically safe circuit the internal stored energy, voltage and current of the interface will not add more than the values specified in Clause 5.7 of EN 60079-11: 2012 to the parameters of the circuit into which it is connected.

The hazardous area terminals are also considered suitable for the connection of an external intrinsically safe source with a  $U_o = 30V$  and  $I_o = 100mA$  having a source resistance of  $U_o/I_o$  connected to hazardous area terminals 2 w.r.t. 1. The capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area cable must not exceed the values as detailed in the original schedule or the certificate relating to the external intrinsically safe source.

**Load Parameters**

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values:

| GROUP | CAPACITANCE<br>( $\mu F$ ) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu H/ohm$ ) |
|-------|----------------------------|--------------------|------------------------------------|
| IIC   | 6.2                        | 5.01               | 1,351                              |
| IIB*  | 55                         | 20.06              | 5,406                              |
| IIA   | 1,000                      | 40.12              | 10,813                             |
| I     | 1,000                      | 65.82              | 17,740                             |

\* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- 1) The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- 2) The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than  $1\mu\text{F}$  for Groups IIB, IIA & I and  $600\text{nF}$  for Group IIC.

## 16 Report Number

See Certificate History

## 17 Specific Conditions of Use

None

## 18 Essential Health and Safety Requirements

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product:

| Clause | Subject                                            | Compliance                    |
|--------|----------------------------------------------------|-------------------------------|
| 1.2.7  | LVD type requirements                              | Manufacturer responsibility   |
| 1.2.8  | Overloading of equipment (protection relays, etc.) | User/Installer responsibility |
| 1.4.1  | External effects                                   | User/Installer responsibility |
| 1.4.2  | Aggressive substances, etc.                        | User/Installer responsibility |

## 19 Drawings and Documents

| Number     | Sheet  | Issue | Date  | Description                                            |
|------------|--------|-------|-------|--------------------------------------------------------|
| CI4500-100 | 1 of 1 | 2     | 1.13  | MTL 4500 Case                                          |
| CI4541YA-1 | 1 & 2  | 1     | 11.14 | Certification Diagram for MTL4541YA                    |
| CI4541YA-2 | 1 & 2  | 1     | 10.14 | MTL4541YA Parts List                                   |
| CI4541YA-3 | 1 of 1 | 1     | 11.14 | Track Layout for MTL4541YA                             |
| CI4541YA-4 | 1 & 2  | 1     | 10.14 | MTL4541YA Component Layout                             |
| CI4541YA-5 | 1 of 1 | 1     | 10.14 | PCB Detail for TPL300                                  |
| CI4541YA-6 | 1 of 1 | 1     | 10.14 | PCB Detail for TPL301                                  |
| CI4541YA-7 | 1 of 1 | 3     | 2.23  | MTL4541YA Certification Label Details – Baseefa – Ex i |

The above drawings are associated with BAS23UKEX0026 and held with IECEx Certificate No. IECEx BAS 23.0013.

For certificate history for MTL4541YA Single Channel Current Repeater, 4/20mA Passive Input for Smart Transmitters, see Baseefa15ATEX0034 Issue 1.

**Schedule 6 – MTL5541 / MTL5541-T / MTL5544 Repeater Power Supply,  
4/20mA for 2 or 3-Wire Transmitters**

13

14

**Certificate Number SGS23ATEX0019 – Issue 2**

**15 Description of Product**

The MTL5544 Two Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters is designed to provide a floating d.c. supply for energising two conventional 2 or 3-Wire 4/20mA transmitters or a 'smart' transmitter in the hazardous area and repeat these currents in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area apparatus to the intrinsically safe circuits by the means of limitation of voltage and current. The apparatus also allows bi-directional signal communication between the hazardous and non-hazardous area by the connection of a hand-held communicator (HHC).

The MTL5544 Two Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters comprises four isolating transformers that provide galvanic isolation between the hazardous and non-hazardous area circuitry, zener diode chains and resistors providing voltage and current limitation. The above, together with other electronic components are mounted on a single printed circuit board (PCB) and housed in a moulded plastic enclosure. Polarised plugs and sockets are provided for hazardous and non-hazardous area connections. A power indicator LED is fitted to the top of the equipment.

The MTL5541 Single Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters is a depopulated version of the MTL5544 and has only one channel populated.

The MTL5541-T Single Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters is of similar construction to the MTL5541 variants of the equipment with the same input and output parameters, but has an extended ambient temperature range of -20°C to +65°C.

**Input / Output Parameters**

Non-Hazardous Area Terminals 7 to 14 (10 to 14 on MTL5541 & MTL5541-T models)

$$U_m = 253V$$

The apparatus is designed to operate on the above terminals from a d.c. supply voltage of up to 35V.

Hazardous Area Terminals 2 w.r.t. 1

or

Hazardous Area Terminals 5 w.r.t 4 (MTL5544 model only)

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 93mA & L_i = 0 \\ P_o = 0.65W \end{array}$$

Hazardous Area Terminals 3 w.r.t. 1

or

Hazardous Area Terminals 6 w.r.t 4 (MTL5544 model only)

$$\begin{array}{ll} U_o = 1.1V & U_i = 30V \\ I_o = 53mA & I_i = 121mA \\ P_o = 15mW \\ C_i = 0 \\ L_i = 0 \end{array}$$

When an intrinsically safe source is connected to these terminals it should have a source resistance of  $U_i / I_i$  and the capacitance and either the inductance or inductance to resistance ratio ( $L/R$ ) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source.

Hazardous area terminals 2 and 5 must not be used when the source is connected to these terminals.

Hazardous Area Terminals 2 w.r.t. 3

or

Hazardous Area Terminals 5 w.r.t 6 (MTL5544 model only)

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 87mA & L_i = 0 \\ P_o = 0.61W & \end{array}$$

On the MTL5544 each channel must be considered as a separate intrinsically safe circuit.

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed must not exceed the following values for either channel:

| GROUP                                             | CAPACITANCE<br>( $\mu$ F) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu$ H/ohm) |
|---------------------------------------------------|---------------------------|--------------------|-----------------------------------|
| Hazardous Area Terminals 2 w.r.t. 1 or 5 w.r.t. 4 |                           |                    |                                   |
| IIC                                               | 0.083                     | 4.2                | 56                                |
| IIB*                                              | 0.65                      | 12.6               | 210                               |
| IIA                                               | 2.15                      | 33.6               | 444                               |
| I                                                 | 3.76                      | 53.7               | 668                               |

| GROUP                                             | CAPACITANCE<br>( $\mu$ F) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu$ H/ohm) |
|---------------------------------------------------|---------------------------|--------------------|-----------------------------------|
| Hazardous Area Terminals 3 w.r.t. 1 or 6 w.r.t. 4 |                           |                    |                                   |
| IIC                                               | 100                       | 12.8               | 2,438                             |
| IIB*                                              | 1,000                     | 47.8               | 8,932                             |
| IIA                                               | 1,000                     | 104.7              | 18,140                            |
| I                                                 | 1,000                     | 156.2              | 28,229                            |
| Hazardous Area Terminals 2 w.r.t. 3 or 5 w.r.t. 6 |                           |                    |                                   |
| IIC                                               | 0.083                     | 4.9                | 59                                |
| IIB*                                              | 0.65                      | 20.0               | 222                               |
| IIA                                               | 2.15                      | 40.9               | 469                               |
| I                                                 | 3.76                      | 59.1               | 710                               |

\* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- 1) The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- 2) The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than 1 $\mu$ F for Groups IIB, IIA & I and 600nF for Group IIC.

The values of  $L_o$  and  $C_o$  determined by this method shall not be exceeded by the sum of all the  $L_i$  plus cable inductances in the circuit and the sum of all of the  $C_i$  plus cable capacitances respectively.

## 16 Report Number

See Certificate History

## 17 Specific Conditions of Use

None

## 18 Essential Health and Safety Requirements

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product:

| Clause | Subject                                            | Compliance                    |
|--------|----------------------------------------------------|-------------------------------|
| 1.2.7  | LVD type requirements                              | Manufacturer responsibility   |
| 1.2.8  | Overloading of equipment (protection relays, etc.) | User/Installer responsibility |
| 1.4.1  | External effects                                   | User/Installer responsibility |
| 1.4.2  | Aggressive substances, etc.                        | User/Installer responsibility |

## 19 Drawings and Documents

New drawings submitted for this issue of certificate.

| Number     | Sheet  | Issue | Date  | Description                    |
|------------|--------|-------|-------|--------------------------------|
| CI4541-1   | 1 of 8 | 5     | 12.23 | Parts List for MTL4541/MTL4544 |
| CI4541-T-2 | 1 of 1 | 2     | 12.23 | Parts List for MTL5541-T       |

Current drawings also associated with this certificate.

| Number     | Sheet   | Issue | Date     | Description                                                         |
|------------|---------|-------|----------|---------------------------------------------------------------------|
| CI4541-1   | 2 of 8  | 5     | 07.09    | Circuit Diagram for the MTL 4541/4544                               |
| CI4541-1   | 3 of 8  | 5     | 07.09    | Circuit Diagram for the MTL 4541/4544                               |
| CI4541-1   | 4 of 8  | 5     | 1.18     | MTL4541/MTL4544 Track Layout                                        |
| CI4541-1   | 4A of 8 | 5     | 1.18     | MTL4541/MTL4544 Track Layout                                        |
| CI4541-1   | 5 of 8  | 6     | 1.13     | MTL4541 Component Layout                                            |
| CI4541-1   | 6 of 8  | 2     | 1.07     | PCB Detail for TPL300                                               |
| CI4541-1   | 7 of 8  | 2     | 1.07     | PCB Detail for TPL301                                               |
| CI4541-T-1 | 1 & 2   | 1     | 1.18     | Circuit Diagram for the MTL5541-T                                   |
| CI4541-T-3 | 1 & 2   | 1     | 1.18     | MTL5541-T Track Layout                                              |
| CI4541-T-4 | 1 of 1  | 1     | 1.18     | MTL5541-T Component Layout                                          |
| CI4541-T-6 | 1 of 1  | 1     | 1.18     | PCB Detail for TPL300                                               |
| CI4541-T-7 | 1 of 1  | 1     | 1.18     | PCB Detail for TPL301                                               |
| CI5541-T-1 | 1 of 1  | 3     | 2.23     | MTL5541-T Certification Label Details & DIN Rail Fittings - Baseefa |
| CI4500-3   | 1 of 1  | 1     | 12.10    | MTL4500 and MTL5500 – Alternative Zener Diode (Panjit)              |
| CI4500-5   | 1 of 1  | 1     | 11.10    | MTL5500 - Alternative DIN Rail Mechanism                            |
| CI4500-6   | 1 of 1  | 1     | 20.12.10 | MTL4500 and MTL5500 – Conformal Coating                             |
| CI5500-100 | 1 of 1  | 3     | 1.13     | New 5500 Outline                                                    |
| CI5541-1   | 1 of 1  | 7     | 2.23     | MTL5541 Certification Label Details & DIN Rail Fittings - Baseefa   |

The above drawings are associated with BAS23UKEX0026 and held with IECEx Certificate No. IECEx BAS 23.0013.

For certificate history for MTL5541 / MTL5541-T / MTL5544 Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters, see Baseefa07ATEX0213 Issue 7.

**Schedule 7 – MTL5541A / MTL5541AS Single Channel & MTL5544A /  
MTL5544AS Two Channel Current Repeater**

13

14

**Certificate Number SGS23ATEX0019 – Issue 2**

**15 Description of Product**

The MTL5544A Two Channel Current Repeater is designed to repeat up to two 4-20mA current signals from separately powered 4/20mA transmitters located in the hazardous area to unspecified apparatus in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area apparatus to the intrinsically safe circuits by the means of limitation of current and voltage. The apparatus also allows bi-directional signal communication between the hazardous and non-hazardous area by connection of a hand-held communicator (HHC).

The MTL5544A Current Repeater comprises four isolating transformers that provide galvanic isolation between the hazardous and non-hazardous area circuitry, fuses, zener diodes and resistors providing voltage and current limitation on each channel. The above, together with other electronic components are mounted on a single printed circuit board (PCB) and housed in a moulded plastic enclosure. Polarised plug and sockets are provided for hazardous and non-hazardous area connections. The apparatus is fitted with a Power-on LED indication.

The MTL5541A Single Channel Current Repeater is a depopulated version of the MTL5544A and has only one channel populated.

Minor changes to the non-hazardous are circuitry of both models of the apparatus from the MTL5541AS Single Channel and MTL5544AS Two Channel Current Repeater. These models use the same common PCB and enclosure and in terms of intrinsic safety are identical.

**Input/Output Parameters**

Non-Hazardous Area Terminals 8, 9, 11, 12, 13 & 14)

$$U_m = 253V \text{ r.m.s.}$$

The circuit connected to non-hazardous area terminals 8, 9, 11, 12, 13 & 14 is designed to operate from a d.c. supply voltage of up to 35V.

Hazardous Area Terminals 2 w.r.t. 1 (Channel 1)

Or

Hazardous Area Terminals 5 w.r.t. 4 (Channel 2 – MTL5544A / 5544AS models only)

$$\begin{array}{ll} U_o = 8.6V \text{ (Diode)} & C_i = 0 \\ I_o = 0 & L_i = 0 \\ P_o = 0 & \end{array}$$

This output voltage does not contribute to the short circuit spark risk, but must be considered for the calculation of load capacitance.

Although the apparatus does not itself comply with the simple apparatus requirements of Clause 5.7 of EN 60079-11: 2012, when each hazardous area channel is connected in an intrinsically safe circuit the internal stored energy, voltage and current of the interface will not add more than the values specified in Clause 5.7 of EN 60079-11: 2012 to the parameters of the circuit into which it is connected.

Each hazardous area channel is also considered suitable for the connection of an external intrinsically safe source with a  $U_o = 30V$  and  $I_o = 100mA$  having a source resistance of  $U_o/I_o$  to be connected to hazardous area terminals 2 w.r.t. 1 - Channel 1 and 5 w.r.t. 4 – Channel 2.

The capacitance and either the inductance or inductance to resistance ratio ( $L/R$ ) of the hazardous area cable must not exceed the values as detailed in the original schedule or the certificate relating to the external intrinsically safe source.

Each channel must be considered as a separate intrinsically safe circuit.

Hazardous Area Terminals 5 w.r.t. 1 (Channels 1 & 2 combined with Terminals 2 & 4 connected together – MTL5544A / 5544AS models only)

$$\begin{aligned}U_o &= 17.2V \text{ (Diode)} & C_i &= 0 \\I_o &= 0 & L_i &= 0 \\P_o &= 0\end{aligned}$$

This output voltage does not contribute to the short circuit spark risk, but must be considered for the calculation of load capacitance.

The connection of channel 1 and 2 together is also considered suitable for the connection of an external intrinsically safe source with a  $U_o = 30V$  and  $I_o = 100mA$  having a source resistance of  $U_o/I_o$  to be connected to hazardous area terminals 5 w.r.t. 1.

The capacitance and either the inductance or inductance to resistance ratio ( $L/R$ ) of the hazardous area cable must not exceed the values as detailed in the original schedule or the certificate relating to the external intrinsically safe source.

### Load Parameters

The capacitance and either the inductance or inductance to resistance ratio ( $L/R$ ) of the hazardous area load connected to the apparatus must not exceed the following values:

| GROUP                                                                                                 | CAPACITANCE<br>( $\mu F$ ) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu H/ohm$ ) |
|-------------------------------------------------------------------------------------------------------|----------------------------|--------------------|------------------------------------|
| Hazardous Area Terminals 2 w.r.t. 1 (Channel 1) or 5 w.r.t. 4 (Channel 2 – MTL5544A/44AS models only) |                            |                    |                                    |
| IIC                                                                                                   | 6.2                        | 5.01               | 1,351                              |
| IIB*                                                                                                  | 55                         | 20.06              | 5,406                              |
| IIA                                                                                                   | 1,000                      | 40.12              | 10,813                             |
| I                                                                                                     | 1,000                      | 65.82              | 17,740                             |
| Hazardous Area Terminals 5 w.r.t. 1 (Channels 1 & 2 combined – MTL5544A/44AS models only)             |                            |                    |                                    |
| IIC                                                                                                   | 0.36                       | 5.01               | 675                                |
| IIB*                                                                                                  | 2.11                       | 20.06              | 2,703                              |
| IIA                                                                                                   | 8.7                        | 40.12              | 5,406                              |
| I                                                                                                     | 12.16                      | 65.82              | 8,870                              |

\*Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

### Notes:

- The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than  $1\mu F$  for Groups IIB, IIA & I and  $600nF$  for Group IIC.

## 16 Report Number

See Certificate History

## 17 Specific Conditions of Use

None

## **18 Essential Health and Safety Requirements**

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product:

| <b>Clause</b> | <b>Subject</b>                                     | <b>Compliance</b>             |
|---------------|----------------------------------------------------|-------------------------------|
| 1.2.7         | LVD type requirements                              | Manufacturer responsibility   |
| 1.2.8         | Overloading of equipment (protection relays, etc.) | User/Installer responsibility |
| 1.4.1         | External effects                                   | User/Installer responsibility |
| 1.4.2         | Aggressive substances, etc.                        | User/Installer responsibility |

## **19 Drawings and Documents**

| <b>Number</b> | <b>Sheet</b> | <b>Issue</b> | <b>Date</b> | <b>Description</b>                                                 |
|---------------|--------------|--------------|-------------|--------------------------------------------------------------------|
| CI5541-2      | 1 of 1       | 4            | 2.23        | MTL5541A Certification Label Details & DIN Rail Fittings - Baseefa |
| CI4541-2      | 1 of 8       | 1            | 10.08       | Parts List for MTL4541A/MTL4544A                                   |
| CI4541-2      | 2 of 8       | 1            | 11.08       | Certification Diagram for MTL4544A & 4541A                         |
| CI4541-2      | 3 of 8       | 1            | 11.08       | Certification Diagram for MTL4544A & 4541A                         |
| CI4541-2      | 4 of 8       | 1            | 11.08       | MTL4541A & 4544A Track Layout                                      |
| CI4541-2      | 5 of 8       | 2            | 1.13        | MTL4541A & MTL4544A Component Layout                               |
| CI4541-2      | 6 of 8       | 1            | 11.08       | PCB Detail for TPL300                                              |
| CI4541-2      | 7 of 8       | 1            | 11.08       | PCB Detail for TPL301                                              |
| CI4500-3      | 1 of 1       | 1            | 12.10       | MTL4500 and MTL5500 – Alternative Zener Diode (Panjit)             |
| CI4500-5      | 1 of 1       | 1            | 11.10       | MTL5500 - Alternative DIN Rail Mechanism                           |
| CI4500-6      | 1 of 1       | 1            | 20.12.10    | MTL4500 and MTL5500 – Conformal Coating                            |
| CI5500-100    | 1 of 1       | 3            | 1.13        | New 5500 Outline                                                   |

The above drawings are associated with BAS23UKEX0026 and held with IECEx Certificate No. IECEx BAS 23.0013.

For certificate history for MTL5541A / MTL5541AS Single Channel & MTL5544A / MTL5544AS Two Channel Current Repeater, see Baseefa08ATEX0322 Issue 3.

**Schedule 8 – MTL5541S, MTL5541S-T, MTL5544S, MTL5544D &  
MTL5544D-L Repeater Power Supplies, 4/20mA**

13

14

**Certificate Number SGS23ATEX0019 – Issue 2**

**15 Description of Product**

The MTL5544S Two Channel Repeater Power Supply, 4/20mA for ‘Smart’ Transmitters is designed to provide floating d.c. supplies for energising two ‘Smart’ 4/20mA Transmitters located in the hazardous area and repeat these currents in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area apparatus to the intrinsically safe circuits by means of limitation of current and voltage. The apparatus also allows bi-directional signal communication between the hazardous and non-hazardous area by the connection of a hand-held communicator (HHC).

The MTL5544S Two Channel Repeater Power Supply, 4/20mA for ‘Smart’ Transmitters comprises four isolating transformers that provide galvanic isolation between the hazardous and non-hazardous area circuitry, zener diode chains and resistors providing voltage and current limitation. The above, together with other electronic components are mounted on a single printed circuit board (PCB) and housed in a moulded plastic enclosure. Polarised plugs and sockets are provided for hazardous and non-hazardous area connections. LED indication is fitted to indicate power-on.

The MTL5541S Single Channel Repeater Power Supply, 4/20mA for ‘Smart’ Transmitters is a depopulated version of the MTL5544S and has only one channel populated.

The MTL5541S-T Single Channel Repeater Power Supply, 4/20mA for ‘Smart’ Transmitters is of a similar construction to the MTL5541S variant of the equipment with the same input and output parameters, but has an extended ambient temperature range of -20°C to +65°C.

The MTL5544D Repeater Power Supply, 4/20mA for 2 or 3 Wire Transmitters with two outputs is designed to provide a floating d.c. supplies for energising a 2 or 3-Wire 4/20mA Transmitter located in the hazardous area and repeat the current on two channels in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area apparatus to the intrinsically safe circuits by means of limitation of current and voltage. The apparatus also allows bi-directional signal communication between the hazardous and non-hazardous area by the connection of a hand-held communicator (HHC). The apparatus uses the same printed circuit board and enclosure as the MTL5544S but is populated with only one hazardous area transmitter connection and two non-hazardous area outputs fitted.

The MTL5544D-L Repeater Power Supply, 4/20mA for 2 or 3 Wire Transmitters is of a similar construction to the MTL5544D variant of the equipment with the same input and output parameters, but has an extended ambient temperature range of -40°C to +60°C.

**Input/Output Parameters**

Non-hazardous Area Terminals 8, 9, 11, 12, 13 & 14

$$U_m = 253V \text{ r.m.s.}$$

The apparatus is designed to operate on non-hazardous area terminals 8, 9, 11, 12, 13 & 14 from a d.c. supply voltage of up to 35V.

Hazardous Area Terminals 2 w.r.t. 1 (Channel 1)

Or

Hazardous Area Terminals 5 w.r.t. 4 (Channel 2 – MTL5544S model)

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 93mA & L_i = 0 \\ P_o = 0.65W & \end{array}$$

Hazardous Area Terminals 3 w.r.t. 1 (Channel 1)

Or

Hazardous Area Terminals 6 w.r.t. 4 (Channel 2 – MTL5544S model)

$U_o = 1.1V$        $U_i = 30V$        $C_i = 0$   
 $I_o = 53mA$        $I_i = 121mA$        $L_i = 0$   
 $P_o = 15mW$

Although the apparatus does not comply with the simple apparatus requirements of Clause 5.7 of EN 60079-11: 2012, when terminals 3 w.r.t. 1 or terminals 6 w.r.t. 4 (MTL5544S model only) are connected in an intrinsically safe circuit the internal stored energy, voltage and current of the interface will not add more than the values specified in Clause 5.7 of EN 60079-11: 2012 to the parameters of the circuit into which it is connected.

When an external intrinsically safe source is connected to these terminals it should have a source resistance of  $U_i / I_i$  and the capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source. Hazardous area terminals 2 and 5 must not be used when the source is connected.

Hazardous Area Terminals 2 w.r.t. 3 (Channel 1)

Or

Hazardous Area Terminals 5 w.r.t. 6 (Channel 2 – MTL5544S model)

$U_o = 28V$        $C_i = 0$   
 $I_o = 87mA$        $L_i = 0$   
 $P_o = 0.61W$

Each channel must be considered as a separate intrinsically safe circuit.

The capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values for either channel:

| GROUP                                                             | CAPACITANCE<br>( $\mu F$ ) | INDUCTANCE<br>(mH) | OR<br>L/R RATIO<br>( $\mu H/\Omega$ ) |
|-------------------------------------------------------------------|----------------------------|--------------------|---------------------------------------|
| Hazardous Area Terminals 2 w.r.t. 1 or 5 w.r.t. 4 (MTL5544S only) |                            |                    |                                       |
| IIC                                                               | 0.083                      | 4.2                | 56                                    |
| IIB*                                                              | 0.65                       | 12.6               | 210                                   |
| IIA                                                               | 2.15                       | 33.6               | 444                                   |
| I                                                                 | 3.76                       | 53.7               | 668                                   |
| Hazardous Area Terminals 3 w.r.t. 1 or 6 w.r.t. 4 (MTL5544S only) |                            |                    |                                       |
| IIC                                                               | 100                        | 12.8               | 2,438                                 |
| IIB*                                                              | 1,000                      | 47.8               | 8,932                                 |
| IIA                                                               | 1,000                      | 104.7              | 18,140                                |
| I                                                                 | 1,000                      | 156.2              | 28,229                                |
| Hazardous Area Terminals 2 w.r.t. 3 or 5 w.r.t. 6 (MTL5544S only) |                            |                    |                                       |
| IIC                                                               | 0.083                      | 4.9                | 59                                    |
| IIB*                                                              | 0.65                       | 20.0               | 222                                   |
| IIA                                                               | 2.15                       | 40.9               | 469                                   |
| I                                                                 | 3.76                       | 59.1               | 710                                   |

\* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than 1 $\mu F$  for Groups IIB, IIA & I and 600nF for Group IIC.

**16 Report Number**

See Certificate History

**17 Specific Conditions of Use**

None

**18 Essential Health and Safety Requirements**

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product:

| Clause | Subject                                            | Compliance                    |
|--------|----------------------------------------------------|-------------------------------|
| 1.2.7  | LVD type requirements                              | Manufacturer responsibility   |
| 1.2.8  | Overloading of equipment (protection relays, etc.) | User/Installer responsibility |
| 1.4.1  | External effects                                   | User/Installer responsibility |
| 1.4.2  | Aggressive substances, etc.                        | User/Installer responsibility |

**19 Drawings and Documents**

New drawings submitted for this issue of certificate:

| Number      | Sheet  | Issue | Date  | Description                                                               |
|-------------|--------|-------|-------|---------------------------------------------------------------------------|
| CI4541-3    | 1 of 8 | 5     | 12.23 | Parts List for MTL4541S, MTL5541S, MTL4544S, MTL5544S, MTL4544D, MTL5544D |
| CI4541S-T-2 | 1 of 1 | 2     | 12.23 | Parts List for MTL5541S-T                                                 |

Current drawings which remain unaffected by this issue:

| Number      | Sheet  | Issue | Date     | Description                                                                                   |
|-------------|--------|-------|----------|-----------------------------------------------------------------------------------------------|
| CI4541S-T-1 | 1 & 2  | 1     | 3.17     | Circuit Diagram for the MTL5541S-T                                                            |
| CI4541S-T-3 | 1 of 1 | 1     | 3.17     | Track Layout for MTL5541S-T                                                                   |
| CI4541S-T-4 | 1 of 1 | 1     | 3.17     | Component Layout for MTL5541S-T                                                               |
| CI4541S-T-6 | 1 of 1 | 1     | 3.17     | PCB Detail for TPL300                                                                         |
| CI4541S-T-7 | 1 of 1 | 1     | 3.17     | PCB Detail for TPL301                                                                         |
| CI5541S-T-1 | 1 of 1 | 2     | 2.23     | MTL5541S-T IECEx Certification Label Details and DIN Rail Fittings - Baseefa                  |
| CI4541-3    | 2 of 8 | 2     | 10.12    | Circuit Diagram for the MTL 4541S, MTL5541S, MTL4544S, MTL5544S, MTL4544D, MTL5544D, MTL4541T |
| CI4541-3    | 3 of 8 | 2     | 10.12    | Circuit Diagram for the MTL 4541S, MTL5541S, MTL4544S, MTL5544S, MTL4544D, MTL5544D, MTL4541T |
| CI4541-3    | 4 of 8 | 1     | 6.09     | Track Layout for MTL4541S, MTL5541S, MTL4544S, MTL5544S, MTL4544D, MTL5544D                   |
| CI4541-3    | 5 of 8 | 4     | 7.23     | Component Layout for MTL4541S, MTL4541T, MTL5541S, MTL4544S, MTL5544S, MTL4544D, MTL5544D     |
| CI4541-3    | 6 of 8 | 1     | 6.09     | PCB Detail for TPL300                                                                         |
| CI4541-3    | 7 of 8 | 1     | 6.09     | PCB Detail for TPL301                                                                         |
| CI4500-3    | 1 of 1 | 1     | 12.10    | MTL4500 and MTL5500 – Alternative Zener Diode (Panjit)                                        |
| CI4500-5    | 1 of 1 | 1     | 11.10    | MTL5500 - Alternative DIN Rail Mechanism                                                      |
| CI4500-6    | 1 of 1 | 1     | 20.12.10 | MTL4500 and MTL5500 – Conformal Coating                                                       |

| Number     | Sheet  | Issue | Date | Description                                                                            |
|------------|--------|-------|------|----------------------------------------------------------------------------------------|
| CI5500-100 | 1 of 1 | 3     | 1.13 | New 5500 Outline                                                                       |
| CI5541-4   | 1 of 1 | 6     | 7.23 | MTL5541S, MTL5544S, MTL5544D Certification Label Details & DIN Rail Fittings - Baseefa |

The above drawings are associated with BAS23UKEX0026 and held with IECEx Certificate No. IECEx BAS 23.0013. For certificate history for MTL5541S, MTL5541S-T, MTL5544S & MTL5544D Repeater Power Supplies, 4/20mA, see Baseefa09ATEX0156 Issue 7.

## 20 Certificate History

| Certificate No.                                                    | Date            | Comments                                                                                                                                                                                                                                                                                                     |
|--------------------------------------------------------------------|-----------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| SGS23ATEX0019                                                      | 3 May 2023      | The release of the prime certificate. The associated test and assessment against the requirements of EN IEC 60079-0:2018 and EN 60079-11: 2012 is documented in Test Report No. GB/BAS/ExTR23.0019/00, Project File No. 22/0560.                                                                             |
| SGS23ATEX0019 Issue 1                                              | 30 August 2023  | This issue of the certificate permits the addition of the MTL5544D-L Repeater Power Supply, 4/20mA for 2 or 3 Wire Transmitters variant to the range covered by the certificate.<br><br>The associated assessment is documented in Certification Report No. GB/SGS/ExTR23.0073/00, Project File No. 23/0360. |
| SGS23ATEX0019 Issue 2                                              | 8 February 2024 | To permit a minor change to the product design and drawings not affecting the certification assessment.<br><br>The associated assessment is documented in Certification Report No. GB/SGS/ExTR24.0008/00, Project File No. 23/0605.                                                                          |
| For drawings applicable to each issue, see original of that issue. |                 |                                                                                                                                                                                                                                                                                                              |